

DIP switch programmering batteriladdare LM1024 (CBHF1-SM 36V)

Per 17-11-01. Batteriexpressen AB.

Dipswitch	Kurva	Batterityp
ON ON ON ON	0	IUa SO
OFF ON ON ON	1	IUIa Acd
ON OFF ON ON	2	IUUa (2,45VPC) Underhållsfritt syrabatteri
OFF OFF ON ON	3	IUUa (2,40VPC) Gel med låg kapacitet
ON ON OFF ON	4	IUUa/0 Acd
OFF ON OFF ON	5	IUUa (2,45VPC) + float charge a 2,30VPC per Underhållsfritt syrabatteri
ON OFF OFF ON	6	IUU0 Gel, Batteriexpressen AGM
OFF OFF OFF ON	7	IUIa PZV Gel
ON ON ON OFF	8	IUIa GNB
OFF ON ON OFF	9	IU0 (2,35VPC) Öppet fritt ventilerat syrabatteri
ON OFF ON OFF	10	IUIa Drysale (HAGEN)
OFF OFF ON OFF	11	IUIa Gel GEL batterier från Batteriexpressen,PartSmart, Sonnenschein
ON ON OFF OFF	12	IUa per Acd (2,40VPC) da underhållsfritt Start-Stop
OFF ON OFF OFF	13	IUIa Optima

DIP 5	DIP 6	Strömstyrka
ON	ON	4A
OFF	ON	5A
ON	OFF	6A
OFF	OFF	7A

DIP 7	DIP 8	Volt
ON	ON	12V
OFF	ON	24V
ON	OFF	36V
OFF	OFF	48V